Error message "Autoboot failed ... /unix : execute format error

Published 07/18/2003

Symptom(s):

```
Error message "Autoboot failed ... /unix : execute format error
Error: "Autoboot failed: pci(0)scsi(0)disk(1)rdisk(0)partition(0)/unix: no such file or directory"
Error:  "Autoboot failed: scsi(0)disk(1)rdisk(0)partition(0)/unix: no such file or directory"
Operating system reinstall did not resolve problem.
Replacing system disk did not help
printenv output:
     SystemPartition=xio(0)pci(15)scsi(0)disk(1)rdisk(0)partition(8)
     OSLoadPartition=xio(0)pci(15)scsi(0)disk(1)rdisk(0)partition(0)
     OSLoadFilename=
     OSLoader=sash
The command resetenv does not correctly configure OSLoadFilename environment variable
```

Fact(s):

```
Silicon Graphics Octane
Silicon Graphics Indigo
Silicon Graphics Indigo2
Silicon Graphics Indy
Silicon Graphics O2
Silicon Graphics O2
Silicon Graphics Octane2
Irix
```

SGI Solution:

```
Change the OSLoadFilename value to point to the kernel, 'unix'
1.From command monitor
>setenv OSLoadFilename /unix
2.  To save this change permanently, also enter 'init'
>init
3.  Reboot the system via 'Start System' Option in the PROM.
```

Additional Details

Creation Date	07/18/2003 11:37 AM
Last modification	09/20/2015 05:32 PM
Published Date	07/18/2003
Products	• Servers and Clusters • SGI Origin/Onyx • Origin/Onyx Server • Software • Legacy Software • Operating Systems • IRIX • Workstations • SGI Tezro • O2 • Octane
Categories	• Knowledgebase • Technical Solution